



(11)

EP 0 946 076 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:

10.01.2007 Bulletin 2007/02

(51) Int Cl.:

H04Q 7/38 (2006.01)

(21) Application number: **99302018.9**

(22) Date of filing: **16.03.1999**

(54) Method and apparatus for interfrequency handoff in a wireless communication system

Verfahren und Vorrichtung zum Interfrequenzweiterreichen in einem drahtlosen
Kommunikationssystem

Procédé et dispositif de transfert interféquence dans un système de communication sans fil

(84) Designated Contracting States:
DE FI FR GB SE

(30) Priority: **26.03.1998 US 48626**

(43) Date of publication of application:
29.09.1999 Bulletin 1999/39

(73) Proprietor: **LUCENT TECHNOLOGIES INC.**
Murray Hill, New Jersey 07974-0636 (US)

(72) Inventors:

- Bernstein, Neil E.
Same,
New Jersey 07981 (US)
- Kuo, Wen Yi
Parsippany,
New Jersey 07054 (US)
- Meyers, Martin Howard
Montclair,
New Jersey 07043 (US)
- Wang, Xiao
Morristown,
New Jersey 07960 (US)

- Weaver, Carl Francis
Morris Plains,
New Jersey 07950 (US)
- Wu, Xiao Cheng
Parsippany,
New Jersey 07054 (US)

(74) Representative: **Sarup, David Alexander et al**
Lucent Technologies EUR-IP UK Ltd
Unit 18, Core 3
Workzone
Innova Business Park
Electric Avenue
Enfield, EN3 7XB (GB)

(56) References cited:

WO-A-95/12297 **GB-A- 2 313 740**
GB-A- 2 314 734 **US-A- 5 640 414**

- **YANG J ET AL: "DESIGN ASPECTS AND SYSTEM EVALUATIONS OF IS-95 BASED CDMA SYSTEMS" IEEE INTERNATIONAL CONFERENCE ON UNIVERSAL PERSONAL COMMUNICATIONS, US, NEW YORK, IEEE, vol. CONF. 6, 12 October 1997 (1997-10-12), pages 381-385, XP000777849 ISBN: 0-7803-3777-8**

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 0 946 076 B1

Description

Field of the Invention

[0001] The present invention relates generally to wireless communication systems and more particularly to techniques for performing inter-frequency handoffs in wireless code division multiple access (CDMA) systems and other types of wireless systems.

Background of the Invention

[0002] An important issue in IS-95 CDMA cellular and Personal Communications Service (PCS) wireless communication systems involves frequency handoffs between adjacent cells or antenna sectors. Each of the cells in such a system generally includes a base station, and the base station associated with a given cell may include an omnidirectional antenna or a multiple-sector directional antenna for communicating with mobile stations such as portable telephone handsets. As a mobile station moves throughout the system, its position relative to the system base stations changes, such that an ongoing call or other communication may need to be handed off from one base station to another, or from one antenna sector to another. Adjacent base stations and antenna sectors are typically configured to utilize different communication frequencies in order to minimize effects such as co-channel interference. Handoffs from one cell or sector to another may therefore involve changing the communication channel frequency from a current frequency to a new frequency. Such handoffs are generally referred to as inter-frequency or other-frequency handoffs.

[0003] A number of techniques have been proposed for improving the efficiency and success rate of inter-frequency handoffs in IS-95 CDMA systems. These techniques utilize messages such as Extended Handoff Direction Messages (EHDMS), Other Frequency Neighbor List Messages (OFNLMs), Other Frequency Neighbor List Response Messages (OFNLRMs) and Other Frequency Report Messages (OFRMs) to implement inter-frequency handoffs. Although proposed techniques based on these messages can reduce the number of call drops during a frequency transition, these techniques still suffer from a number of drawbacks. For example, the OFRM message is presently configured to allow a mobile station to report a signal-to-noise measure which is both "interference limited" in that it will typically decrease as the mobile moves across same-frequency cell boundaries, and "noise limited" in that it will also decrease as the mobile moves across other-frequency cell boundaries. For a measure which is interference limited, interference due to signals generated by other cells is greater than the noise level, while for a measure which is noise limited, the noise level is greater than the interference due to signals generated by other cells. A same-frequency cell boundary may be defined by a set of points at which the strength of a pilot signal from one cell exceeds

that of a pilot signal from an adjacent cell, where both the pilot signals are at the same frequency. An other-frequency cell boundary may be defined as a set of points at which a signal from one cell at a designated frequency exceeds the strength of a signal from an adjacent cell at another frequency by a specified number of decibels. An OFRM message which utilizes conventional signal-to-noise measures cannot be used to distinguish same-frequency cell boundaries from other-frequency cell boundaries, and therefore does not provide an optimal trigger for inter-frequency handoffs.

[0004] In addition, the above-noted message-based techniques will often involve a base station commanding a mobile station to perform a periodic search for a new frequency as soon as the mobile station enters into a transition area near the edge of a new cell or sector. However, this periodic search tends to degrade voice quality of an ongoing call, while also reducing the speed of the search for new potential base stations at the current frequency. Moreover, in many practical applications, this periodic search for a new frequency can be unnecessary if the mobile is operating under certain types of radio frequency (RF) conditions. Yet another significant problem with the above-noted techniques is that the techniques may increase the likelihood of "ping-ponging" or rapid switching between the new frequency and the current frequency. More particularly, it may be possible in some areas of the system that both the new frequency and the current frequency will have good RF coverage, which could lead to ping-ponging if, for example, the mobile station reports the received power and signal-to-noise measure for only the new frequency.

[0005] International (PCT) patent publication WO 95/12297 and United Kingdom published patent application GB-A-2313740 disclose conventional handoff processes and trigger metrics. It is known from GB-A-2313740 to provide a method of controlling a frequency handoff in a wireless communication system in which a mobile station communicates with one or more base stations, the method comprising the steps of:

generating a trigger metric; and
utilizing the trigger metric to control a handoff from a current frequency to a new frequency in an ongoing call.

Summary of the Invention

[0006] The present invention is characterised over the disclosure of GB-A-2313740 in that said trigger metric is generated as a function of an average transmit signal-to-noise measure for a plurality of pilot signals and a sum of the signal-to-noise measures for at least a subset of the plurality of pilot signals.

Summary of the Invention

[0007] In accordance with a first aspect of the inven-

tion, a noise-limited coverage trigger is provided which may be used to distinguish between same-frequency cell boundaries, which are generally interference limited, and other-frequency cell boundaries, which are generally noise limited. The coverage trigger is used to control inter-frequency handoffs, and can be implemented using signal-to-noise measurements performed in a mobile station. In an illustrative embodiment, the coverage trigger may be generated as the difference between the average transmit signal-to-noise measure for all significant pilots and the linear sum of significant pilot signal-to-noise measures reported in a Power Measurement Report Message (PMRM) or Pilot Strength Measurement Message (PSMM) transmitted from the mobile station.

[0008] Alternative embodiments may utilize the mobile receive power alone as a trigger metric. For example, a measure of mobile receive power incorporated into a PSMM can be used to trigger a handoff to another frequency using a "database" approach. In this approach, when the mobile receive power in a given cell becomes small and the mobile sees primarily border cell pilots, a particular pilot is selected from a list of neighbor pilots stored in a database for that cell, and the mobile is instructed to perform a "blind" handoff to the selected pilot at the new frequency. In this manner, a mobile can be instructed to perform a handoff to a new frequency without taking any pilot E_c/I_o measurements at the new frequency. The mobile receive power can also be used in the mobile to filter periodic reports. For example, the mobile may only make PSMM reports when the mobile receive power drops below a threshold, which may be specified by the current cell site.

[0009] Other aspects of the invention provide alternative techniques for controlling inter-frequency handoffs in a wireless communication system. These techniques can substantially eliminate unnecessary periodic searches in a frequency transition area, while also reducing the likelihood of ping-ponging between a current frequency and a new frequency. In an illustrative embodiment, the invention involves adding additional field parameters to an Extended Handoff Direction Message (EHDM) of an IS-95 CDMA system. The additional field parameters include one or more thresholds which ensure that a mobile station initiates a search for a new frequency, for example, only if its received power at the current frequency is lower than a certain threshold, or if a sum of signal-to-noise values for its active pilot signals at the current frequency is less than a certain threshold. The mobile can also be configured to operate such that if the received power at the new frequency does not exceed the received power at the current frequency by a designated hysteresis amount, then a search is not performed in the new frequency. The invention thus provides additional checking criteria for use in inter-frequency handoffs to ensure that unnecessary tuning and search in the new frequency is avoided.

[0010] Further improvements can be provided in inter-frequency handoffs in other illustrative embodiments of

the invention. For example, a mobile station in an area in which a transition is to be made from a current frequency to a new frequency is configured to report received power and signal-to-noise values for both the new frequency and the current frequency. If these values indicate that the mobile station is operating under acceptable RF conditions at the current frequency, there is no need to perform an inter-frequency handoff. This aspect of the invention can substantially reduce the likelihood of ping-ponging between the current and new frequencies, as compared to the conventional inter-frequency handoff techniques noted above.

Brief Description of the Drawings

[0011]

FIG. 1 shows an exemplary code division multiple access (CDMA) wireless communication system in which inter-frequency handoffs in accordance with the invention may be implemented.

FIG. 2 is a block diagram showing an exemplary mobile station which can perform inter-frequency handoffs in accordance with the invention.

FIGS. 3A and 3B show a flow diagram illustrating a frequency handoff process which may be implemented in the mobile station of FIG. 2 in accordance with one aspect of the invention.

Detailed Description of the Invention

[0012] The present invention will be illustrated below in conjunction with an exemplary IS-95 code division multiple access (CDMA) wireless communication system. It should be understood, however, that the invention is not limited to use with any particular type of communication system, but is instead more generally applicable to any wireless system in which it is desirable to provide improved performance for frequency handoffs. For example, although the techniques are illustrated with reference to the IS-95 CDMA cellular and personal communications service (PCS) systems, it will be apparent to those skilled in the art that the techniques are also applicable to other CDMA systems, as well as to other types of wideband and narrowband wireless systems. The term "primary base station" as used herein refers generally to a base station communicating directly with a given mobile station, such as the base station handling an on-going call for the mobile station. The term "current frequency" refers generally to the channel frequency used by a mobile station for an ongoing call or other communication. The term "new frequency" refers to a potential channel frequency to which an ongoing call or other communication may be handed off as the mobile station moves within the wireless system.

[0013] FIG. 1 shows an exemplary cellular or personal communication services (PCS) system 10. The system 10 is configured in accordance with TIA/EIA/IS-95A, "Mo-

mobile Station - Base Station Compatibility Standard for Dual-Mode Wideband Spread Spectrum Cellular System," June 1996, and ANSI J-STD-008, "Personal Station - Base Station Compatibility Requirements for 1.8 to 2.0 GHz Code Division Multiple Access (CDMA) Personal Communication Systems," both of which are incorporated by reference herein. The system 10 includes a mobile station (MS) 12 and a number of base stations BS 1, BS2, BS3 and BS4. The base station BS1 of FIG. 1 represents a primary base station, communicating with mobile station 12 via the path designated by solid two-way arrow 24, while the surrounding base stations BS2, BS3 and BS4 may serve as secondary base stations which can detect signals transmitted via the paths indicated by dashed one-way arrows 26. The primary base station BS 1 communicates with the mobile station 12 using CDMA techniques described in the above-cited standards documents. As the mobile station 12 moves within the system 10, handoffs occur, such that base stations other than BS1 become primary base stations for communicating with the mobile station 12. The system 10 in this illustrative embodiment also includes first and second mobile switching centers (MSCs) 14-1 and 14-2. A given MSC typically connects several BSs with a public switched telephone network (PSTN) 16. For example, MSC 14-1 connects base stations BS1 and BS2 with the PSTN 16 and MSC 14-2 connects base stations BS3 and BS4 with the PSTN 16. The system 10 also includes a memory 18 having a number of registers including a home location register (HLR) 20 and a visitor location register (VLR) 22. The HLR 20 and VLR 22 store user data and billing information for each mobile station 12 of the system 10.

[0014] FIG. 2 shows a more detailed view of the mobile station 12. The mobile station 12 includes an antenna 32 which receives signals from and transmits signals to base stations of the system 10. A receive signal is directed by a diplexer filter 33 to an input of a receiver 34 which may implement conventional downconversion, demodulation, digital-to-analog conversion and other processing of the receive signal. A transmitter 35 performs complementary operations such as analog-to-digital conversion, modulation and upconversion to generate a transmit signal which is directed via diplexer 33 to the antenna 32 for transmission. A processor 36 is coupled to both the receiver 34 and the transmitter 35. The processor 36 operates in conjunction with a memory 38 to control the communication functions of the mobile station 12. For example, data or other information in messages which are part of a receive signal may be supplied to processor 36 such that processor 36 can implement the process steps to be described in conjunction with FIGS. 3A and 3B below. The processor 36 may also perform receive signal power and signal-to-noise measurements, and generate messages which are incorporated into the transmit signal for transmission to one or more base stations.

[0015] A first aspect of the invention relates to a noise-limited coverage trigger which, unlike conventional inter-

frequency handoff triggers, may be used to distinguish between "interference-limited" same-frequency cell boundaries, and "noise-limited" other-frequency cell boundaries. The coverage trigger is used to control inter-frequency handoffs, and can be implemented using signal-to-noise measurements performed in a mobile station. As will be described in greater detail below, an exemplary coverage trigger in accordance with the invention may be generated as the difference between the average transmit signal-to-noise measure for all significant pilots and the linear sum of significant pilot signal-to-noise measures reported in otherwise conventional Power Measurement Report Message (PMRM) or Pilot Strength Measurement Message (PSMM) transmitted from the mobile station. For example, an exemplary trigger metric Tn in accordance with the invention may be defined as:

$$Tn = Fe - Es$$

where Fe is the average transmit Ec/I_0 value in dB for all significant pilots, and Es is the linear sum of all significant pilot Ec/I_0 values reported in the PMRM or PSMM messages from the mobile station. The term "significant pilots" refers generally to pilots which are no less than X dB below the largest pilot as measured at the mobile, where X may be approximately six or another suitable value. An Ec/I_0 value for a given pilot is a measure of the ratio of signal energy to interference plus noise at the pilot frequency. A typical handoff threshold for Tn might be between about 3 dB and 5 dB.

[0016] This portion of the description will utilize the notational convention that values expressed in logarithmic quantities (i.e., dB) begin with an upper case character, while values expressed in linear quantities begin with a lower case character. For example, the average fraction fe of transmit power in the pilots may be expressed as $fe = 10^{Fe/10}$. The fraction fe is given by:

$$fe = \sum (e) / \sum (e \cdot f)$$

where e is a sorted $(1, n)$ vector containing all Ec/I_0 values for the significant pilots, f is a $(1, n)$ vector of all transmit Ec/I_0 values corresponding to the elements of e , n is the number of significant pilots as seen from the mobile station, and $e \cdot f$ is an operation which divides each element of e by the corresponding element in f . If e and f have a length of 1 then $fe = f$. The vector f of transmit Ec/I_0 values may be expressed as:

$$f = gp^2 ./ (gp^2 + ga^2 + gs^2 + \sum (gv^2))$$

where gp is a $(1, n)$ vector of pilot gain settings for each cell site corresponding to the elements of e , ga and gs are $(1, n)$ vectors of page and sync channels in digital gain units (DGUs), gv is an (m, n) matrix of voice channel gains, and $\Sigma()$ applied to an (m, n) matrix sums the columns to yield a $(1, n)$ vector. The above-noted linear sum of Ec/I_o values is then given by:

$$es = \sum(e).$$

[0017] The computation of the trigger metric Tn can be repeated periodically, such as about every two to five seconds, when the mobile station is in a frequency transition area. The computed metric is used to determine whether an inter-frequency handoff should take place. For example, a trigger metric having a value which exceeds a threshold may be used to indicate the need for a particular inter-frequency handoff. Unlike conventional handoff triggers, the above-described trigger is able to distinguish same-frequency cell boundaries from other-frequency cell boundaries, and is therefore particularly well suited for use in controlling inter-frequency handoffs.

[0018] Alternative embodiments of the invention may utilize a handoff trigger which is based on mobile receive power alone. For example, a measure of mobile receive power incorporated into a PSMM can be used to trigger a handoff to another frequency using an approach based on neighbor information stored in a database. A handoff which utilizes this approach may be initiated when the mobile receive power in a given cell becomes small and the mobile sees primarily border cell pilots. A border cell may be characterized as a cell which is missing some neighbors on the same frequency. A particular pilot is selected from a list of neighbor pilots stored in a database for the given cell, and the mobile is instructed to perform a "blind" handoff to the selected pilot at the new frequency. In this manner, a mobile can be instructed to perform a handoff to a new frequency without taking any pilot Ec/I_o measurements at the new frequency. The mobile receive power can also be used in the mobile to filter periodic reports. For example, the mobile may only make PSMM reports when the mobile receive power drops below a threshold, which may be specified by the current cell site.

[0019] FIGS. 3A and 3B show a flow chart which illustrates an inter-frequency handoff process in accordance with another aspect of the invention, as carried out by mobile station 12 of system 10 in a frequency transition area. The frequency transition area may be, for example, an area in which the mobile station 12 is approaching the vicinity of one or more base stations while maintaining an ongoing call or other communication with a primary base station. Step 40 of FIG. 3A indicates that the mobile station 12 is communicating with a base station over a CDMA traffic channel. The mobile station 12 in step 42 receives an Other Frequency Neighbor List Message

(OFNLM) from a base station, in step 44 sends out an Other Frequency Neighbor List Response Message (OFNLRM) in response to the OFNLM message, and in step 46 receives an Extended Handoff Direction Message (EHDM). The OFNLM, OFNLRM and EHDM are described in detail in the above-cited IS-95 standard document, and provide information regarding inter-frequency handoff in the CDMA system 10.

[0020] In steps 48 and 50, the mobile station 12 checks whether the received power at the current frequency utilized by the CDMA traffic channel is greater than a threshold $MIN_RX_PWR_CURR$, and whether the sum of Ec/I_o values for the active pilots is greater than a threshold $MIN_SUM_ECIO_CURR$. If either of these checks is not passed, the process moves to step 52 in which the mobile station tunes to a new frequency in order to explore a potential handoff opportunity. If both of the checks of steps 48 and 50 are passed, then the operation of tuning to the new frequency in step 52 is not performed since the mobile station is under acceptable RF conditions at the current frequency. Acceptable RF conditions may be defined as conditions such that the mobile received Ec/I_o value is within Y dB of the transmit Ec/I_o value, where Y is typically 3 or less. The checks of steps 48 and 50 help to eliminate the unnecessary tuning and searching operations typically associated with conventional inter-frequency handoff techniques.

[0021] If either of the checks of steps 48 and 50 are not passed, such that the mobile station tunes to a new frequency in step 52 to explore a potential handoff opportunity, the mobile station then in step 54 checks whether the received power at the new frequency is greater than a threshold $MIN_RX_PWR_NEWF$. The mobile station in step 56 also checks whether the difference between the received power at the new frequency and the received power at the current frequency is greater than a threshold $HYSTERESIS_RX_PWR$. This check serves to further reduce the likelihood that unnecessary tuning and searching operations will be carried out, while also reducing ping-ponging between the current and new frequencies. If either of the checks in steps 54 and 56 is not passed, then the mobile station in step 55 tunes back to the current frequency, and sends an Other Frequency Report Message (OFRM) which reports the following measurements: (1) the received power at the current frequency (RX_PWR_CURR); (2) the received power at the new frequency (RX_PWR_NEWF); and (3) the Ec/I_o values of all active pilots measured at the new frequency. The Ec/I_o value for a given pilot is a measure of the signal energy of that pilot to the noise plus interference at the pilot frequency. Other types of signal-to-noise measures may also be used.

[0022] If both of the checks in steps 54 and 56 are passed, then the mobile station performs a search for a new active set of frequencies and/or a neighbor list for the new frequency. In step 58, a determination is made as to whether the new active set is empty. If the new active set is empty, the mobile station searches in step

59 for other flagged pilots in the OFNLM message received in step 42. Additional details regarding this type of searching in an IS-95 CDMA system can be found in the above-cited IS-95 standard document and, for example, E. Tiedemann and T. Chen, "Inter-Frequency Hard Handoff Improvements (Rev. 2)," Qualcomm contribution to TR45.5, TR45.5.3.1/97.03.20.02, March 20, 1997, and P. Jain et al., "Proposed IS-95-B Text for Inter-Frequency Hard Handoff Improvements," Qualcomm contribution to TR45.5/97.03.20.03, March 17-21, 1997, which are incorporated by reference herein.

[0023] If the new active set is not empty, the mobile station in step 60 checks whether the sum of E_c/I_o values for all of the active pilots in the new active set is greater than a threshold $MIN_SUM_ECIO_NEWF$. If the check of step 60 is not passed, the process goes to step 59 to search for other flagged pilots in the OFNLM message. If the check of step 60 is passed, the mobile station in step 62 uses the new active set while also searching for other flagged pilots in the OFNLM message. A determination is made in step 64 as to whether the mobile station has received a "good" frame within a designated waiting period MAX_WAIT . A good frame is generally one in which substantially all of the bits in the frame have been received correctly. If a good frame is received within the MAX_WAIT period, the mobile station in step 66 completes the inter-frequency handoff by sending an HCM, and continues the ongoing call on the new frequency.

[0024] If a good frame is not received within the MAX_WAIT period in step 64, or after the search for other pilots in step 59 is commenced, the process moves to step 70 of FIG. 3B. If the search for other pilots is determined in step 70 to be the first search after receipt of the EHDM in the mobile station, the mobile station in step 71 tunes back to the current frequency, and sends an OFRM which reports the following measurements: (1) the received power at the current frequency (RX_PWR_CURR); (2) the received power at the new frequency (RX_PWR_NEWF); (3) the E_c/I_o values of all active pilots at the current frequency; and (4) the E_c/I_o values of all active pilots at the new frequency. Providing this information in the OFRM ensures that the base station will have better control on the handoff trigger. Step 71 is also performed if an "always report" condition is determined to exist in step 72, or if the sum of the E_c/I_o values of the flagged pilots in the OFNLM message is greater than a threshold $MIN_SUM_ECIO_NEWF$ in step 74. In the "always report" condition, a flag will be set which tells the mobile to send an OFRM regardless of whether or not the sum of the new frequency pilots is above a threshold. If none of the conditions in steps 70, 72 and 74 are met, the mobile station tunes back to the current frequency in step 76, and then continues the call at the current frequency, as shown in step 78.

[0025] As noted previously, if both of the checks of steps 48 and 50 are passed, then the tuning to the new frequency in step 52 is not performed since the mobile station is under acceptable RF conditions at the current

frequency. The process instead moves to step 80 of FIG. 3B. If step 80 indicates that the process is on its first search for other flagged pilots after receipt of the EHDM in the mobile station, the mobile station in step 82 sends an OFRM which reports the following measurements: (1) the received power at the current frequency (RX_PWR_CURR); and (2) the E_c/I_o values of all active pilots at the current frequency.

[0026] A determination is then made in step 84 as to whether periodic search is to be performed. Performance of periodic search may be specified by a flag which is set to indicate that the mobile will search the new frequency periodically without further instructions to search. If periodic search is not being performed, the mobile station continues the call at the current frequency as shown in step 86. If periodic search is being performed, the mobile station continues the call at the current frequency as shown in step 78, as long as step 88 indicates that the current time modulo the designated search period is not equal to zero. When the time modulo the search period is equal to zero in step 88, the process returns to step 48 of FIG. 3A. Step 84 and its subsequent operations are also performed if either of the checks in steps 54 and 56 is not passed, after the mobile station in step 55 tunes back to the current frequency and sends the above-noted OFRM reporting RX_PWR_CURR , RX_PWR_NEWF and the E_c/I_o values of all active pilots measured at the new frequency.

[0027] The inter-frequency handoff process described above in conjunction with FIGS. 3A and 3B may be implemented by altering otherwise conventional IS-95 EHDM and OFRM to include a number of additional fields for providing the above-noted thresholds. For example, the EHDM may be modified to include the threshold $MIN_RX_PWR_CURR$ used in step 48, the threshold $MIN_SUM_ECIO_CURR$ used in step 50, and the threshold $HYSTERESIS_RX_PWR$ used in step 56. The OFRM could be modified such that it includes fields for measurements such as RX_PWR_CURR , RX_PWR_NEWF , the E_c/I_o values of all active pilots at the current frequency, and the E_c/I_o values of all active pilots at the new frequency, as shown in step 71. The inter-frequency handoff process of FIGS. 3A and 3B can thus be implemented using simple modifications to message formats in conjunction with appropriate programming of software, firmware or hardware in processor 36 and memory 38 of the mobile station 12.

[0028] The foregoing description of the invention is intended to be illustrative only. For example, it should be noted that the EHDM, OFRM and other messages utilized in the above description are exemplary only, and the inter-frequency handoff techniques of the invention may be incorporated using other types of messages or signaling and with other types of wireless systems. In addition, the E_c/I_o measurements reported by a mobile station may be replaced with other types of signal-to-noise measurements or mobile received power measurements. These and numerous other alternative em-

bodiments within the scope of the following claims will be readily apparent to those skilled in the art.

Claims

1. A method of controlling a frequency handoff in a wireless communication system (10) in which a mobile station (12) communicates with one or more base stations (BS1, BS2, BS3, BS4), the method comprising the steps of:

generating a trigger metric; and
utilizing the trigger metric to control a handoff from a current frequency to a new frequency in an ongoing call; **CHARACTERIZED IN THAT** said trigger metric is generated as a function of an average transmit signal-to-noise measure for a plurality of pilot signals and a sum of the signal-to-noise measures for at least a subset of the plurality of pilot signals.

2. A method as claimed in claim 1 wherein the trigger metric is generated as the difference between an average transmit signal-to-noise measure for the plurality of pilot signals and a linear sum of pilot signal-to-noise measures for the plurality of pilot signals.

3. A method as claimed in claim 1 wherein the signal-to-noise measures are generated in the mobile station (12) and included in messages transmitted from the mobile station.

4. A method as claimed in claim 3 wherein the system is an IS-95 CDMA system and the messages transmitted from the mobile station (12) include at least one of a Power Measurement Report Message (PM-RM) and a Pilot Strength Measurement Message (PSMM).

5. A method as claimed in claim 1 wherein the trigger metric is configured so as to distinguish same-frequency cell boundaries from other-frequency cell boundaries.

6. Apparatus for use in controlling frequency handoffs in a wireless communication system (10) in which a mobile station (12) communicates with one or more base stations (BS1, BS2, BS3, BS4), the apparatus comprising:

a processor (36) for generating a trigger metric; and
a memory (38) for at least temporarily storing a representation of the trigger metric, such that the trigger metric is used to control a handoff from a current frequency to a new frequency in

an ongoing call in the system; **CHARACTERIZED IN THAT**

said processor is adapted to generate the trigger metric as a function of an average transmit signal-to-noise measure for a plurality of pilot signals and a sum of the signal-to-noise measures for at least a subset of the plurality of pilot signals.

7. Apparatus as claimed in claim 6 wherein the trigger metric is generated as the difference between an average transmit signal-to-noise measure for the plurality of pilot signals and a linear sum of pilot signal-to-noise measures for the plurality of pilot signals.

8. Apparatus as claimed in claim 6 wherein the signal-to-noise measures are generated in the mobile station (12) and included in messages transmitted from the mobile station.

9. Apparatus as claimed in claim 8 wherein the system is an IS-95 CDMA system and the messages transmitted from the mobile station (12) include at least one of a Power Measurement Report Message (PM-RM) and a Pilot Strength Measurement Message (PSMM).

10. Apparatus as claimed in claim 6 wherein the trigger metric is configured so as to distinguish same-frequency cell boundaries from other-frequency cell boundaries.

Patentansprüche

1. Verfahren zur Steuerung eines Frequenzweiterreichens in einem drahtlosen Kommunikationssystem (10), in welchem eine Mobilstation (12) mit einer oder mehreren Basisstationen (BS1, BS2, BS3, BS4) kommuniziert, wobei das Verfahren die folgenden Schritte umfasst:

- Erzeugen einer Triggermetrik und
- Verwenden der Triggermetrik zur Steuerung eines Weiterreichens einer Verbindung von einer aktuellen Frequenz zu einer neuen Frequenz während eines laufenden Gesprächs, **dadurch gekennzeichnet, dass**
- die Triggermetrik in Abhängigkeit von einer mittleren Sendesignal-Rauschmessung für mehrere Pilotsignale und einer Summe der Signal-Rauschmessungen für mindestens eine Untermenge der mehreren Pilotsignale erzeugt wird.

2. Verfahren nach Anspruch 1, wobei die Triggermetrik als die Differenz zwischen einer mittleren Sendesi-

gnal-Rauschmessung für die mehreren Pilotsignale und einer linearen Summe von Pilotsignal-Rauschmessungen für die mehreren Pilotsignale erzeugt wird.

3. Verfahren nach Anspruch 1, wobei die Signal-Rauschmessungen in der Mobilstation (12) erzeugt und in von der Mobilstation gesendete Meldungen eingebunden werden.
4. Verfahren Anspruch 3, wobei das System ein IS-95 CDMA-System ist und die von der Mobilstation (12) gesendeten Meldungen mindestens eine Power Measurement Report Message PMRM (Berichtsmeldung zur Leistungsmessung) und/oder eine Pilot Strength Measurement Message PSMM (Messwertmeldung zur Pilotsignalstärke) umfassen.
5. Verfahren nach Anspruch 1, wobei die Triggermetrik derart konfiguriert ist, dass Zellengrenzen gleicher Frequenz von Zellengrenzen anderer Frequenz unterschieden werden.
6. Gerät zum Einsatz bei der Steuerung von Frequenzweiterreichungen in einem drahtlosen Kommunikationssystem (10), in welchem eine Mobilstation (12) mit einer oder mehreren Basisstationen (BS1, BS2, BS3, BS4) kommuniziert, wobei das Gerät umfasst:
 - einen Prozessor (36) zur Erzeugung einer Triggermetrik und
 - einen Speicher (38) zur mindestens temporären Speicherung einer Darstellung der Triggermetrik in einer Weise, dass die Triggermetrik zur Steuerung eines Weiterreichens einer Verbindung von einer aktuellen Frequenz zu einer neuen Frequenz während eines laufenden Gesprächs im System benutzt wird, **dadurch gekennzeichnet, dass**
 - der Prozessor angepasst ist, um die Triggermetrik in Abhängigkeit von einer mittleren Sendesignal-Rauschmessung für mehrere Pilotsignale und einer Summe der Signal-Rauschmessungen für mindestens eine Untermenge der mehreren Pilotsignale erzeugt wird.
7. Gerät nach Anspruch 6, wobei die Triggermetrik als die Differenz zwischen einer mittleren Sendesignal-Rauschmessung für die mehreren Pilotsignale und einer linearen Summe von Signal-Rauschmessungen für die mehreren Pilotsignale erzeugt wird.
8. Gerät nach Anspruch 6, wobei die Sendesignal-Rauschmessungen in der Mobilstation (12) erzeugt und in von der Mobilstation gesendete Meldungen eingebunden werden.
9. Gerät nach Anspruch 8, wobei das System ein IS-

95 CDMA-System ist und die von der Mobilstation (12) gesendeten Meldungen mindestens eine Power Measurement Report Message PMRM (Berichtsmeldung zur Leistungsmessung) und/oder eine Pilot Strength Measurement Message PSMM (Messwertmeldung zur Pilotsignalstärke) umfassen.

10. Gerät nach Anspruch 6, wobei die Triggermetrik derart konfiguriert ist, dass Zellengrenzen gleicher Frequenz von Zellengrenzen anderer Frequenz unterschieden werden.

Revendications

1. Procédé de commande d'un transfert intercellulaire de fréquence dans un système de communication sans fil (10) dans lequel une station mobile (12) communique avec une ou plusieurs stations de base (BS1, BS2, BS3, BS4), le procédé comprenant les étapes de :

génération d'une métrique de déclencheur ; et utilisation de la métrique de déclencheur pour commander un transfert intercellulaire d'une fréquence actuelle à une nouvelle fréquence dans un appel en cours ; **CARACTERISE EN CE QUE**

ladite métrique de déclencheur est générée en fonction d'une mesure de signal sur bruit de transmission moyenne pour une pluralité de signaux pilotes et une somme des mesures de signal sur bruits pour au moins un sous-ensemble de la pluralité de signaux pilotes.

2. Procédé selon la revendication 1 dans lequel la métrique de déclencheur est générée comme la différence entre une mesure de signal sur bruit de transmission moyenne pour la pluralité de signaux pilotes et une somme linéaire de mesures de signal sur bruit pilote pour la pluralité de signaux pilotes.
3. Procédé selon la revendication 1 dans lequel les mesures de signal sur bruit sont générées dans la station mobile (12) et comprises dans des messages transmis depuis la station mobile.
4. Procédé selon la revendication 3 dans lequel le système est un système CDMA IS-95 et les messages transmis depuis la station mobile (12) comprennent au moins un parmi un message de signalement de mesure de puissance (PMRM) et un message de mesure d'intensité pilote (PSMM).
5. Procédé selon la revendication 1 dans lequel la métrique de déclencheur est configurée de façon à distinguer des limites de cellules de même fréquence de limites de cellules d'autres fréquences.

6. Appareil pour une utilisation dans la commande de transferts intercellulaires de fréquence dans un système de communication sans fil (10) dans lequel une station mobile (12) communique avec une ou plusieurs stations de base (BS1, BS2, BS3, BS4), l'appareil comprenant :

un processeur (36) pour générer une métrique de déclencheur ; et
 une mémoire (38) pour stocker au moins temporairement une représentation de la métrique de déclencheur, de telle sorte que la métrique de déclencheur est utilisée pour commander un transfert intercellulaire d'une fréquence actuelle à une nouvelle fréquence dans un appel en cours dans le système ; **CARACTERISE EN CE QUE**
 ledit processeur est apte à générer la métrique de déclencheur en fonction d'une mesure de signal sur bruit de transmission moyenne pour une pluralité de signaux pilotes et une somme des mesures de signal sur bruit pour au moins un sous-ensemble de la pluralité de signaux pilotes.

7. Appareil selon la revendication 6 dans lequel la métrique de déclencheur est générée comme la différence entre une mesure de signal sur bruit de transmission moyenne pour la pluralité de signaux pilotes et une somme linéaire de mesures de signal pilote sur bruit pour la pluralité de signaux pilotes.
8. Appareil selon la revendication 6 dans lequel les mesures de signal sur bruit sont générées dans la station mobile (12) et comprises dans des messages transmis depuis la station mobile.
9. Appareil selon la revendication 8 dans lequel le système est un système CDMA IS-95 et les messages transmis depuis la station mobile (12) comprennent au moins un parmi un message de signalement de mesure de puissance (PMRM) et un message de mesure d'intensité pilote (PSMM).
10. Appareil selon la revendication 6 dans lequel la métrique de déclencheur est configurée de façon à distinguer des limites de cellules de même fréquence de limites de cellules d'autres fréquences.

FIG. 1




FIG. 2




FIG. 3A




FIG. 3B

